

PD415

DMR handheld radio



DMR radio with integrated RFID reader

The PD415 DMR handheld radio gives you conventional DMR radio and an integrated RFID reader. As part of the Hytera Patrol System it is the ideal radio for security personnel who patrol complex buildings.

Patrol system

The Hytera Patrol System is a patrol system for the management of patrol information. This solution enables the positions of security personnel to be monitored centrally and in real time on a digital map.

Long battery service life

With its battery service life of up to 16 hours in digital mode, the PD415 shows stamina and is therefore reliable even when deployed for long periods.

Technical data PD415

General data	
Frequency range	VHF: 136 – 174 MHz UHF: 400 – 470 MHz
Supported operating modes	<ul style="list-style-type: none"> ▪ DMR Tier II (conventional DMR) ▪ Simulcast ▪ Analog DMR Tier II according to ETSI TS 102 361-1/2/3
Number of channels	256 (128 analog + 128 digital)
Number of zones	3
Channel spacing	12.5 / 25 kHz
Operating voltage	7.4 V (nominal)
Standard battery	1500 mAh (lithium-ion battery)
Battery service life (5-5-90 duty cycle, high transmitting power, standard battery)	analog / digital: approx. 12 / 16 hours (with 1500 mAh) approx. 16 / 22 hours (with 2000 mAh)
Frequency stability	± 0.5 ppm
Antenna impedance	50 Ω
Dimensions (H × B × T, without antenna)	112 x 54 x 28 mm
Weight (with antenna and standard battery)	approx. 270 g
Programmable keys	2
Range of the RFID reader	Up to 4 cm

Environmental conditions	
Operating temperature range	-30 °C to +60 °C
Storage temperature range	-40 °C to +85 °C
ESD	IEC 61000-4-2 (Level 4), ± 8 kV (contact), ± 15 kV (air)
Protection against dust and moisture	IP54
Shock and vibration resistance	MIL-STD-810 C / D / E / F / G
Relative humidity	MIL-STD-810 C / D / E / F / G

Transmitter	
Transmitting power	VHF: 1 / 5 W UHF: 1 / 4 W
Modulation	11 K0F3E at 12.5 kHz 16 K0F3E at 25 kHz
4FSK digital modulation	12.5 kHz (data only): 7K60FXD 12.5 kHz (data and voice): 7K60FXW
Interfering signals and harmonics	- 36 dBm (< 1 GHz) - 30 dBm (> 1 GHz)
Modulation limiting	± 2.5 kHz at 12.5 kHz ± 5.0 kHz at 25 kHz
Noise cancellation	40 dB at 12.5 kHz 45 dB at 25 kHz
Adjacent channel selectivity	60 dB at 12.5 kHz 70 dB at 25 kHz
Audio sensitivity	+ 1 dB to - 3 dB
Nominal audio distortion	≤ 3 %
Digital vocoder type	AMBE +2™

Receiver	
Sensitivity (analog)	0.22 µV (12 dB SINAD) 0.22 µV (typical) (12 dB SINAD) 0.4 µV (20 dB SINAD)
Sensitivity (digital)	0.22 µV / BER 5 %
Adjacent channel selectivity TIA-603 ETSI	60 dB at 12.5 kHz / 70 dB at 25 kHz 60 dB at 12.5 kHz / 70 dB at 25 kHz
Intermodulation TIA-603 ETSI	70 dB at 12.5 / 25 kHz 70 dB at 12.5 / 25 kHz
Spurious response rejection TIA-603 ETSI	70 dB at 12.5 / 25 kHz 70 dB at 12.5 / 25 kHz
Signal-noise ratio (S/N)	40 dB at 12.5 kHz 45 dB at 25 kHz
Nominal audio power output	0.5 W
Nominal audio distortion	≤ 3 %
Audio sensitivity	+ 1 dB to - 3 dB
Conducted spurious emission	< - 57 dBm

All technical information was determined at the factory and in accordance with the corresponding standards. Subject to change on the basis of continuous development.



Hytera Mobilfunk GmbH

Address: Fritz-Hahne-Straße 7, 31848 Bad Münder, Germany
Tel.: + 49 (0)5042 / 998-0 Fax: + 49 (0)5042 / 998-105
E-mail: info@hytera.de | www.hytera-mobilfunk.com



SGS Certificate DE11/81829313

Hytera Mobilfunk GmbH reserves the right to modify the product design and the specifications. In case of a printing error, Hytera Mobilfunk GmbH does not accept any liability. All specifications are subject to change without notice.

Encryption features are optional and have to be configured separately; they are also subject to German and European export regulations.

HYT Hytera are registered trademarks of Hytera Co. Ltd. ACCESSNET® and all derivatives are protected trademarks of Hytera Mobilfunk GmbH. © 2017 Hytera Mobilfunk GmbH. All rights reserved.